

Recommended Circuit Breaker for Baykal Pressbrakes

Disclaimer- These circuit breaker ratings are a suggestion only and can vary. Consideration must be given to cable size; the type of installation and voltage drop on the particular circuit as determined in AS3008/2017. This can be determined by a qualified electrician.

Pressbrakes						
Stock code	Model No.	Voltage	Full load current	Circuit breaker	Type of breaker	Cable 5 Core 3ph + N + E
S897C	APHS 31090	415	18.5 amp	25 amp	D curve	Yes
S884D	APHS 31120	415	24.3 amp	32 amp	D curve	Yes
S884F	APHS 31120	415	24.3 amp	32 amp	D curve	Yes
S884S	APHS 31120	415	24.3 amp	32 amp	D curve	Yes
S885D	APHS 31160	415	31 amp	40 amp	D curve	Yes
S885E	APHS 31160	415	31 amp	40 amp	D curve	Yes
S885F	APHS 31160	415	31 amp	40 amp	D curve	Yes
S885G	APHS 31160	415	31 amp	40 amp	D curve	Yes
S887	APHS-C 31160	415	31 amp	40 amp	D curve	Yes
S889C	APHS 41160	415	31 amp	40 amp	D curve	Yes
S889D	APHS 41160	415	31 amp	40 amp	D curve	Yes
S896A	APHS 41200	415	36.9 amp	50 amp	D curve	Yes